



HARRIS CORPORATION
BROADCAST DIVISION
QUINCY, IL 62305

THIS DOCUMENT CONTAINS PROPRIETARY DATA OF HARRIS CORPORATION. NO DISCLOSURE, REPRODUCTION, OR USE OF ANY PART THEREOF MAY BE MADE EXCEPT BY WRITTEN PERMISSION.

Dwg: 817-2335-003
Sh: 1 of 8

REVISIONS

Rev:	Date:	Dfm:	Eng:	ECO No:	Rev:	Date:	Dfm:	Eng:	ECO No:
------	-------	------	------	---------	------	-------	------	------	---------

APPROVALS

Drawn By: R. SPRENGER 10-11-93	Eng: D. KOONTZ 10-11-93	Proj Eng: E. TWITCHELL 10-11-93	Mfg: M. RUSSELL 10-11-93
--------------------------------	-------------------------	---------------------------------	--------------------------

Frequency (MHz)	A7 (PLL) Dip Switch Setting										A3 (Digital Modulator) Dip Switch Setting											
	M9	M8	M7	M6	M5	M4	M3	M2	M1	M0	N11	N10	N9	N8	N7	N6	N5	N4	N3	N2	N1	N0
Exciter Output																						
87.9	1	0	0	0	0	1	1	0	0	0	1	0	1	1	1	0	1	1	1	0	0	0
88	1	0	0	0	0	1	1	0	0	1	1	0	0	1	1	1	0	0	0	1	0	0
88.1	1	0	0	0	1	0	0	0	0	0	0	1	1	1	1	1	0	1	0	0	0	0
88.2	1	0	0	0	1	0	0	0	0	1	0	1	0	1	1	1	0	1	1	1	0	0
88.3	1	0	0	0	1	0	0	0	1	0	0	0	1	1	1	1	0	1	1	0	0	0
88.4	1	0	0	0	1	0	0	0	1	0	1	0	1	1	1	0	1	1	1	0	0	0
88.5	1	0	0	0	1	0	0	0	1	1	1	0	0	1	1	1	0	0	0	1	0	0
88.6	1	0	0	0	1	0	0	1	0	0	0	1	1	1	1	1	0	1	0	0	0	0
88.7	1	0	0	0	1	0	0	1	0	1	0	1	0	1	1	1	0	1	1	1	0	0
88.8	1	0	0	0	1	0	0	1	1	0	0	0	1	1	1	1	1	0	1	0	0	0
88.9	1	0	0	0	1	0	0	1	1	0	1	0	1	1	1	0	1	1	1	0	0	0
89	1	0	0	0	1	0	0	1	1	1	1	0	0	1	1	1	0	0	0	1	0	0
89.1	1	0	0	0	1	0	1	0	0	0	0	1	1	1	1	1	0	1	0	0	0	0
89.2	1	0	0	0	1	0	1	0	0	1	0	1	0	1	1	1	0	1	1	1	0	0
89.3	1	0	0	0	1	0	1	0	1	0	0	0	1	1	1	1	1	0	1	0	0	0
89.4	1	0	0	0	1	0	1	0	1	0	1	0	1	1	1	0	1	1	1	0	0	0
89.5	1	0	0	0	1	1	0	0	0	1	1	0	0	1	1	1	0	0	0	1	0	0
89.6	1	0	0	0	1	1	0	0	1	0	0	1	1	1	1	1	0	1	0	0	0	0
89.7	1	0	0	0	1	1	0	0	1	1	0	1	0	1	1	1	0	1	1	1	0	0

Title: FREQUENCY CHART, DIGIT

Sheet 1 of 8

Rev:

Dwg: 817-2335-003

M